



Key features:

- SkyRadar-DX's operating frequencies are 978MHz and 1090 MHz and the latter conforms to DO-260 standard.
- Artificial horizon information
- Integrated on board WAAS capable (non TSO) 5Hz GPS receiver with remote antenna
- Output data over Wi-Fi network (multiple displays can be connected)
- USB high speed serial port output
- Operates as WiFi access point

- No airspeed input required
 - GPS input is compatible with external antenna
 - Input voltage 11-36 volts
 - Power consumption less than 5 watts
-

The SkyRadar Receiver contains the following major components:

- **UAT (978 MHz) receiver tuned to receive and process ADS-B data**
- 1090 MHz receiver
- **Built-in AHRS module**
- **High accuracy GPS module**
- **WiFi module transmitting data to iPad, iPhone or iPod Touch**

The SkyRadar Receiver also comes with:

- GPS/ADS-B antennas
- Power cable to plug receiver into your plane's 12 or 28 volt cigarette lighter outlet

{niftybox background=ivory, textcolor=maroon, float=center, textalign=justify, border=gold, font=Arial}

Technical Specifications		Standard	DO-282B
Frequency		978 MHz + 1090Mhz	
Sensitivity		-98 dBm	

Input voltage	11-36 Volts
Operating temperature	-15 to +60 C
Power consumption	4 Watts
GPS	

5 Hz update rate WAAS capable receiver

Available outputs	USB (high speed usb serial port), Wi-Fi
Dimensions	6.30 X 3.07 X 1.06"

{/niftybox}

SkyRadar Receiver package contains:

1. SkyRadar-DX Dual Band receiver with built-in AHRS module
2. 2 attachable antennas (978 MHz and 1090 MHz)
3. GPS
4. Power cord to plug receiver into cigarette lighter
5. Startup instructions

2 remote antennas (978 MHz and 1090 MHz) with 2 4ft or 6ft cables can be purchased separately.



