



Key features:

- SkyRadar-D's operating frequencies are 978MHz and 1090 MHz and the latter conforms to DO-260 standard.
- Integrated on board WAAS capable (non TSO) 1Hz GPS receiver with remote antenna
- Output data over Wi-Fi network (multiple displays can be connected)
- USB high speed serial port output
- Input voltage 11-36 volts
- Power consumption less than 5 watts

The SkyRadar Receiver contains the following major components:

- UAT receiver tuned to receive and process ADS-B data
- 1090Mhz receiver
- High accuracy GPS module
- WiFi module transmitting data to iPad, iPhone or iPod Touch

The SkyRadar Receiver also comes with:

- GPS/ADS-B antennas
- Power cable to plug receiver into your plane's 12 or 28 volt cigarette lighter outlet

{niftybox background=ivory, textcolor=maroon, float=center, textalign=justify, border=gold, font=Arial}

Technical Specifications		Standard	DO-282B
Frequency		978 MHz + 1090Mhz	
Sensitivity		-98 dBm to +3dBm	
Input voltage		11-36 Volts	
Operating temperature		-15 to +60 C	
Power consumption		5 Watts	
GPS			

1 Hz update rate WAAS capable receiver

Available outputs	USB (high speed usb serial port), Wi-Fi
Dimensions	6.30 X 3.07 X 1.06"

{/niftybox}

SkyRadar Receiver package contains:

1. SkyRadar-D Dual Band receiver
2. 2 attachable antennas (978 MHz and 1090 MHz)
3. GPS
4. Power cord to plug receiver into cigarette lighter
5. 4 Sticky bumpers
6. Startup instructions

2 remote antennas (978 MHz and 1090 MHz) with 2 4ft or 6ft cables can be purchased separately.

